

# B401.M

## Модуль-переходник Modular adapters

Код / Code	d	D	L	d <sub>1</sub>	D <sub>1</sub>	L <sub>1</sub>	L <sub>2</sub>	Кг/Кг
B401.M.25.030.25	14	25	22	14	-	30	-	0,12
B401.M.25.050.25	14	25	22	14	-	50	-	0,19
B401.M.32.040.25	18	32	28	14	25	40	32	0,19
B401.M.32.070.25	18	32	28	14	25	70	62	0,30
B401.M.32.040.32	18	32	28	18	-	40	-	0,24
B401.M.32.070.32	18	32	28	18	-	70	-	0,42
B401.M.40.040.25	22	40	32	14	25	40	32	0,26
B401.M.40.060.25	22	40	32	14	25	60	52	0,33
B401.M.40.080.25	22	40	32	14	25	80	72	0,40
B401.M.40.040.32	22	40	32	18	32	40	32	0,30
B401.M.40.070.32	22	40	32	18	32	70	62	0,47
B401.M.40.100.32	22	40	32	18	32	100	92	0,64
B401.M.40.050.40	22	40	32	22	-	50	-	0,46
B401.M.40.080.40	22	40	32	22	-	80	-	0,71
B401.M.50.040.25	28	50	38	14	25	40	30	0,39
B401.M.50.060.25	28	50	38	14	25	60	50	0,46
B401.M.50.080.25	28	50	38	14	25	80	70	0,53
B401.M.50.100.25	28	50	38	14	25	100	90	0,60
B401.M.50.040.32	28	50	38	18	32	40	30	0,44
B401.M.50.070.32	28	50	38	18	32	70	60	0,65
B401.M.50.100.32	28	50	38	18	32	100	90	0,77
B401.M.50.050.40	28	50	38	22	40	50	40	0,59
B401.M.50.080.40	28	50	38	22	40	80	70	0,84
B401.M.50.110.40	28	50	38	22	40	110	100	1,09
B401.M.50.060.50	28	50	38	28	-	60	-	0,87
B401.M.50.100.50	28	50	38	28	-	100	-	1,42
B401.M.63.060.40	38	63	46	22	40	60	48	0,96
B401.M.63.090.40	38	63	46	22	40	90	78	1,21
B401.M.63.120.40	38	63	46	22	40	120	108	1,46
B401.M.63.070.50	38	63	46	28	50	70	58	1,26
B401.M.63.100.50	38	63	46	28	50	100	88	1,65
B401.M.63.120.50	38	63	46	28	50	120	108	1,91
B401.M.63.120.63	38	63	46	38	-	120	-	2,76
B401.M.80.120.50	48	80	56	28	50	120	108	2,43
B401.M.80.140.63	48	80	56	38	63	140	128	3,74
B401.M.80.120.80	48	80	56	48	-	120	-	4,56
B401.M.80.160.80	48	80	56	48	-	160	-	6,04

